

AMPLIFIERS/ MIXING AMPLIFIERS/ CA200Z

Applications

- Classrooms
- Meeting rooms
- Multimedia presentations (in combination with video projectors, screens, etc.)
- Retail shops
- Museums and exhibitions
- Integrated AV systems with central remote control system (Crestron®, Extron®, AMX®, etc.)

AV Integration Digital Mixing Amplifier

The CA200z is a compact digital mixing amplifier with 2 x 70 WRMS output zones and 6 audio inputs, together with a full and smart set of remote control options. It is a perfect solution in many applications: an all-in-one audio device in retail shops, multimedia, presentation and education projects that can be perfectly integrated with external control devices, from Ecler and from third-party players.



Key Features

- 4 LINE ST & 2 MIC audio inputs, with independent routing and levels for outputs A and B
- 2 x 70 WRMS @ 4 Ω audio outputs
- STEREO, MONO, BRIDGE or independent ZONES A/B working modes
- 2-level Talkover / Pager priority system
- Additional PAGER input for the connection of the MPAGE4 desktop paging station
- MIC2 and LINE2 inputs doubled on front panel, with jack and mini-jack connectors
- AUX A/B LINE output
- Front panel LCD display
- ON / STANDBY, Signal Present and CLIP LED indicators
- RS-232 interface for external (third-party) remote control. CA-NET protocol compatible
- 2 REMOTE ports included, compatible with Wpm series (0-10 VDC): zone A / zone B volume and source / preset selection
- IR receiver (IR remote control included)
- Auto start-up preset recovery function
- LCD display with ON, OFF and DIMMED idle modes
- Auto stand by function



Main Technical Specifications	POWER 1% THD RMS			
	4Ω per output	70 W		
	8Ω per output	38W		
	8Ω Bridged	97 W		
	Frequency response (-3dB)	15Hz – 40kHz		
	Remote Control	IR remote included + 2 REMOTE ports (selection & volume ctrl.) + RS232 (EclerCOMM and CA-NET Protocol compatible)		
	Dimensions / weight	H: 210 mm	L: 230 mm	W: 88 mm

Accessories

- Wpm series wall panel controls
- MPAGE4 desktop paging station
- MPAGE1 desktop paging station
- 2UHRMKIT optional rack mount kit
- TR2-70 low to high impedance output transformer kit



TR2-70 transformer kit